

Includes:



- PN: 1140950 *PRO-Pointer AT Blackline Edition*
- PN: 2469700 *USB-C Cable*
- PN: 9405500 *Rechargeable USB-C 9V Li-Ion Battery*
- PN: 1620700 *Belt Holster*



The *PRO-Pointer® AT Blackline Edition* is manufactured in the United States of America and in accordance with Garrett's ISO 9001, 14001, and 45001 internationally certified Quality, Environmental, and Safety Management System and meets the following international standards:

- FCC
- CE
- RoHS
- ICNIRP
- IEC 60529-IP68

Specifications

Model Name	<i>PRO-Pointer® AT Blackline Edition</i>		
Model Number	1140950		
Operating Temperatures	14°F (-10°C) to 104°F (40°C)		
Operating Frequency	11.5 kHz		
Waterproof Rating	20 ft (6 m) maximum depth, IP68		
Tuning	Automatic or manual retune		
Indicators	Proportional audio/vibration pulse rate		
Controls	Single-button operation: power, retune, sensitivity adjustment, and audio or vibration alarms		
Dimensions	Length	9" (228.6 mm)	
	Thickness	1.5" (38.1 mm) tapered to 0.9" (22.9 mm)	
Weight	6.5 oz. (0.2 kg) with battery in		
Battery	Single rechargeable USB-C 9V Li-ion battery		
Battery Life	Rechargeable: 30 hours		

Battery Specifications

Name	Power Energy	Rated Capacity	Voltage	Discharge Current (Max)	Charging Current	Indicator Light
9V	4100 mWh	455 mAh	9V	750 mA	360 mA	1. Red Light: Charging 2. Green Light: Charged



Product Features

- Widely applicable: compatible with standard charger models.
- Long-lasting: supplies stable power for extended periods.
- Built-in PCB: located on the positive pole, protects the battery from short circuiting during charging and discharging.
- ABS construction: battery constructed with anti-corrosion, anti-oxidation, explosion-proof, and anti-leak materials.

Precautions

- Do not disassemble or assemble the rechargeable battery
- Do not use or store this rechargeable battery under direct sunlight, near a hot device, or in other high-temperature locations.
- Do not drop the rechargeable battery on the ground or place heavy objects on it.
- Children must use this rechargeable battery under adult supervision.
- It is strictly forbidden to use non-designated chargers to charge this battery.



Warranty



For More Info

Garrett Electronics, Inc.
 1881 W. State St.
 Garland, TX 75042
 +1 (972) 494-6151
 +1 (800) 234-6151 (U.S. and Canada)

1532620 Rev A1, EC-11479 Dec. 2025 © Garrett Electronics, Inc.

GARRETT®

PRO-Pointer® AT Blackline Edition



USER MANUAL



Features

- ❶ Power, Retune, Adjust Button
- ❷ Pinpointing Tip
- ❸ 360° Side-Scan Area
- ❹ Exclusive Scraping Blade
- ❺ LED Flashlight
- ❻ Waterproof Speaker
- ❼ Lanyard Attachment Loop
- ❽ Sealed Battery Cover
- ❾ Ruler in Inches and Centimeters



Powering On

Press and release the button (❶) while holding the detector away from any metallic objects. You will hear 2 beeps and the LED (❺) will remain on.

Powering Off

Press and hold the button for a half second until you hear a single beep (or single vibration in Stealth Mode), indicating power down.

Changing Settings

The *PRO-Pointer AT Blackline Edition* has three Sensitivity settings and two detection settings: Audio-plus-Vibrate or Vibrate-only (silent/stealth).

To enter adjustment mode, press and hold the button (❶) for 2 seconds—indicated by a single beep followed by a dual-tone beep and flashing LED. (Note: In Stealth Mode, beeps are replaced by vibration pulses.)

The first button press after entering adjustment mode indicates the current setting. Repeatedly press the button to cycle through the 6 settings:

- 1 beep = minimum Sensitivity, with audio
- 2 beeps = medium Sensitivity, with audio (Default setting)
- 3 beeps = maximum Sensitivity, with audio
- 1 vibrate = minimum Sensitivity/Stealth
- 2 vibrate = medium Sensitivity/Stealth
- 3 vibrate = maximum Sensitivity/Stealth

To exit adjustment mode, press and hold the button for 2 seconds—indicated by a dual-tone beep (dual vibrate in Stealth Mode), or wait 5 seconds for automatic exit.

Notes:

- Lower Sensitivity settings are recommended to prevent detection of highly mineralized grounds.
- Detection remains operable during the adjustment mode.
- Settings will be remembered when the unit is switched off and back on.

Fast Retune for Mineralized Ground

To tune out the detection of saltwater, wet sand or highly mineralized ground, hold the tip of the *PRO-Pointer AT Blackline Edition* to the water, sand or soil and quick-press the button (❶) for an instant Retune.

If necessary, repeat this Fast Retune to further eliminate any environmental response. Note: An alternate means of eliminating the ground response is to reduce Sensitivity.



Fast Retune feature quickly tunes out mineralized ground, saltwater, wet sand, and other challenging environments.

Precisely Pinpointing Large Targets

Slowly scan toward the object until the response increases to full/constant alarm. Then quick-press the button to instantly retune and narrow the detection field. Continue scanning toward the object to find its precise location. Repeat this Fast Retune to further narrow detection field as needed.

Lost Pinpointer Alarm

After 5 minutes of being ON without a button press, the *PRO-Pointer AT Blackline Edition* will begin emitting progressively faster warning chirps for 60 minutes. Press the power button to reset.

Auto-Off Feature

After one hour of warning chirps, the *PRO-Pointer AT Blackline Edition* will power off automatically.

Scraping Blade

This rugged edge is ideal for sifting through dirt while searching for the target. The *PRO-Pointer AT Blackline Edition's* 360° side-scan detection allows the detector to alarm when the blade is passed in close proximity to a metallic target.

Holster

Secure to any standard size belt. A metal snap within the holster will cause the pinpointer to alarm if put away while powered on.

Ruler

The *PRO-Pointer AT Blackline Edition* has a ruler molded into its exterior to measure a target's depth in either centimeters or inches.

Low Battery Alarm

When the battery becomes low, the detector will sound an alternating dual-tone alarm. Replace the 9V battery as soon as possible.

Battery Replacement

Simply rotate the battery cover counterclockwise to remove and clockwise to tighten by hand. To properly install the 9V battery, match the larger battery terminal to the larger opening in the compartment. Remove the battery when the unit is to be stored more than 30 days.

Rechargeable 9V Battery

The rechargeable 9V lithium battery simple charges with the supplied USB-C charging cable. Charging block is not included. Charges in about 2 hours and provides up to 40 hours use.



Operational Information and Tips

- Operation is completely automatic. All metals will be detected, including ferrous and non-ferrous.
- When a target is detected, the *PRO-Pointer AT Blackline Edition* will produce an audio and/or vibration alert. The rate of the pulsing audio and vibrations increase proportionately as the pinpointer is moved closer to a metallic target.
- Maximum detection of very small targets is obtained against the side about 1/2" from the tip.
- To avoid canceling out a target, do not turn on the *PRO-Pointer AT Blackline Edition* while it is adjacent to the target.